

IPhone App IP Cam Viewer Setup Manual

IP Cam Viewer Pro By NibblesnBits



1. How to get App IPcam viewer

1.1 Go in App store and Search "IP cam Viewer"





1.2 Find App "IP cam Viewer Pro", buy and install it.



2. Installation and Settings

2.1 Add a new camera

Open the app "IP cam Viewer", Click Configure and select "Manage Cameras"(At first time you start the app, it will be assigned some deme cameras from all of the world randomly, you can delete them and add new camera you want)

Loading	Loading	Loading.	
Sapari Gan		3011	Recall Group
			Auto Sequence
Loading			Record Mode
Camera 3			App Settings
			Manage Cameras
Click	here		About
	· ()E)		Æ



2.2 Click "Add Camera" and choose "IP Camera ,DVR,NVR"

Back	Manage Cameras	Done	Back	Manage	Cameras	6 Done
			Cl	hoose ″IP	Camera"	,
			2.	1		
			IP	Camera,	DVR, NV	′R
			G	eneric UR	L	
	Click here to a new camera	ıdd	Tr	affic/Publ	ic Came	ra
			So	can Came	ra	
Options	Groups	d Camera	Options	Groups	1.	Add Camera

2.3 Enter all the informations of the camera and Click "Save" when finish settings.

1) name, as you like.

2)Type, choose model of the camera.

3)IP/Host, In put camera's ip address (local view),or input DDNS for remoter view (My camera ip is 192.168.1.201,only for reference)

4)port, input camera's http port (my camera's port is 201,only for reference)

5)User/Password, Mjpeg series cameras default username is "admin", no password.H.264 default username and password both are "admin".

Save Setup Camera Cancel
Name J011 Name as you like
Type Apexis APM-J011 O Chosse model of the Camera
IP/Host 192.168.1.201 Input Camera's IP address or DDNS
HTTP HTTPS Port 201 Input Camera's http port
User admin Fass password
input Username and Password, More O defalt is admin, no pas sword



Back Select Camera Type	Save Setup Camera Cancel		
APC	Name J011		
Арех	Type Apexis APM-J011 📀		
Apexis Choose "Brand"	IP/Host apexistech.gicp.net		
Aposonic	HTTP HTTPS Port 201		
Appro	User admin Pass password		
	More 📀 Test		
Apexis APM-H804-WS	DDNS for remote view (my Manufacturer's ddns is apexistech.gicp.net,only for reference)		
Apexis APM-J011			
Apexis H Series Choose the Model			
Apexis J Series			

 $2.4\ \mbox{Go}\ \mbox{``back''}\ \mbox{and}\ \mbox{you}\ \mbox{will}\ \mbox{the}\ \mbox{video}\ \mbox{from}\ \mbox{the}\ \mbox{camera}.$

••••• 中国移动	0	And a state of the second	
Back Manage Cameras	Edit	Im.	
J011			get full screen
Go Back when you finish settin	ıgs	JOII	
		Workin	ng!
Options Groups Add C	amera		E



- 3. More settings
- 3.1 It support 2 way audio, snapshot, pt and so on.



3.2 Mosiac viewer

Back Manage Cameras	Edit		
J011	0	JOIT	Loading h804
h804	0		

3.3 Rotate the phone

